



好利科技

股票代码: 002729

扫一扫

获取

更多资讯



锂电池电路 保护解决方案

LITHIUM BATTERY CIRCUIT PROTECTION SOLUTION

三端保险丝广泛用于锂离子电池BMS电路的二次保护上, 是一个同时具备过流、过压保护功能的复合型电路保护器件
主要应用于: 二轮车、清洁电器、储能市场


Three-terminal fuses are widely used in the secondary protection of lithium-ion battery BMS circuits. They are a composite circuit protection device with both overcurrent and overvoltage protection functions. Currently it is mainly used in: two-wheeled vehicles, clean appliances, and energy storage markets.

三端保险丝

优势特点

保护反应速度快 高稳定性

耐脉冲能力强 高可靠性



Unit单位:mm

Model 型号	Rated current 额定电流	Cells in Series 电池串数	Rated voltage 额定电压	Rated breaking capacity 分断能力	Operating voltage 动作电压	Fuse resistance 保险丝内电阻	Safety certification 安规认证	
	(A)	Cell	(Vdc)	(A)	(V)	(mΩ)	UR	TUV
LT-0630	30	1~2	80	80	4.0~9.6	0.5-2.5	●	●
LT-1230	30	3	80	80	8.4~19.1	0.5-2.5	●	●
LT-1830	30	4~5	80	80	10.5~ 23.5	0.5-2.5	●	●
LT-3030	30	6~9	80	80	20.2~ 46.3	0.5-2.5	●	●
LT-4030	30	10~14	80	80	28.0~ 62.0	0.5-2.5	●	●
LT-4530H	30	13	80	80	36.2~ 58.5	0.5-2.5	●	●
LT-5030	30	15~16	80	80	47.2~ 68.0	0.5-2.5	●	●
LT-6030	30	20	80	80	50-74	0.5-2.5	●	●
LT-1245	45	3	80	120	3.5~9.8	0.4-2.0	●	●
LT-1445	45	4	80	120	13.0~18.4	0.4-2.0	●	●
LT-2045	45	5	80	120	16.7~23.5	0.4-2.0	●	●
LT-3045	45	6~7	80	120	22.3~31.5	0.4-2.0	●	●
LT-4045	45	9~10	80	120	33.0~46.9	0.4-2.0	●	●
LT-5045	45	12~14	80	120	43.7~62.0	0.4-2.0	●	●
LT-5245H	45	13~14	80	120	47.2~62.0	0.4-2.0	●	●
LT-5545	45	16	80	120	36.0~62.0	0.4-2.0	●	●
LT-6045	45	20	80	120	50-74	0.4-2.0	●	●
LT-1260	60	3	80	160	3.5~9.8	0.2-1.5	●	●
LT-1460	60	4	80	160	13.0~18.4	0.2-1.5	●	●
LT-2060	60	5	80	160	16.7~23.5	0.2-1.5	●	●